

634 Series

4 Amp Power Controllers



Access control system power requirements are uniquely different from other systems. Unlike camera system power requirements, access control systems draw more current for locking hardware and during access control-related events. 75 – 85% of access control operating problems and technical support calls are due to power issues.* Access control systems require steady and clean (filtered) low-voltage DC current with surge suppression to protect printed circuit boards and connected devices from damage due to dirty power (transients and voltage spikes).

SDC power supplies have been developed specifically to help reduce power system issues and to support electric locks and access control requirements. Our hybrid design combines the efficiency of switching power supplies with the inductive load handling capability of linear power supplies in various 12/24 VDC current output capabilities and enclosure sizes. Filtering and output voltage regulation provide protection and ensure the longevity of all system components.

The high performance, heavy-duty circuitry is ideal for inductive loads and multi-door applications. With the addition of SDC programmable controllers or relay modules, the user-friendly modular designs ensure versatility, interface capability and easy installation of virtually any electric locking devices, access controls and related fire & life safety equipment.

* SDC technical support logs.



MODELS

634RFA 4 Amp DC Power Controller With Large Cabinet



STANDARD FEATURES

- Regulated and filtered linear DC power
- Class 2 outputs
- Field selectable dual voltage
- Fire/emergency release input
- Isolated battery charging circuit
- Low battery disconnect
- Input and output surge protection
- Visual status indicator (LED)
- Cabinet enclosures with pre-configured control module mounting holes



OPTIONAL FEATURES

- 230 VAC, 50/60 Hz input
- Key lock cover
- Fire/emergency release manual reset switch
- System on/off switches
- Choice of compatible door control modules



APPLICATIONS

FIRE/EMERGENCY RELEASE INPUT

A fire alarm input provides simultaneous release of all fail safe locks and door holders in case of an emergency. An optional manual reset switch following a fire/emergency release or power loss is available to meet code compliance. When the optional manual reset feature is required, should an AC power loss occur or the emergency release input be actuated, personnel must restore secondary output power manually at the power supply after the emergency release signal is reset and/or AC power is restored.

ISOLATED BATTERY CHARGING CIRCUIT

A separate charging output provides 13.5 or 27 volts to fully charge the batteries. The secondary output is always precisely maintained at 12 or 24VDC to protect locking devices and components from over voltage while the batteries are charging. The specified secondary output current is also maintained while batteries are charging. Derating of the secondary output current is not required when charging batteries.

LOW BATTERY DISCONNECT

Batteries are disconnected from the output circuit prior to deep discharge, preventing battery destruction. Batteries are not included and should be ordered separately.*

DOOR CONTROL MODULES

Door control relay modules are available to meet virtually any application need. All wiring for lock hardware, access controls, remote controls and monitoring is terminated at one central location. Installation and troubleshooting is simplified. Modules may be factory installed or ordered separately for field installation as needed. Cabinet enclosures are pre-configured with mounting holes to accommodate door control modules. All modules are individually fused for protection of multiple station systems.

* See related products for backup batteries.

INPUT & OUTPUT SURGE PROTECTION

Input and output surge protection is built-in. The AC input voltage is circuit breaker protected and the outputs are PTC protected.

VISUAL STATUS INDICATOR (LED)

LED tri-color status indicators provide information regarding the AC input, DC output and battery backup status. Outputs for remote annunciation are available.

SYSTEM ON/OFF SWITCHES

Optional System On/Off switches are available both inside the cabinet enclosure or on the cabinet enclosure cover.


KEY LOCK COVER

Optional key lock cover available where tamper-resistance is required.

INTERNATIONAL STANDARD INPUT

Additionally an alternative 230VAC international standard input is an available option.

CROSS REFERENCE



	602	631	632	634	636
DC Output Rating	1 Amp	1.5 Amp	2 Amp	4 Amp	6 Amp
Small Cabinet	602RF	631RF	632RF	-----	-----
Large Cabinet	602RFA	631RFA	632RFA	634RFA	636RFA
Less Cabinet	602RFL	631RFL	632RFL	-----	-----
	CLICK TO VIEW	CLICK TO VIEW	CLICK TO VIEW		CLICK TO VIEW

 SPECIFICATIONS

634RFA

Input	115 VAC 1.2 Amp 50/60 Hz
Output	12/24 VDC (1) 4 Amp (2) 2 Amp Class 2
Battery Charger	13.5/27 VDC 500 mA
Cabinet	16" x 14" x 6½" 16 Gauge
Weight	25 lbs

BACKUP BATTERY DISCHARGE TIME

Standby Power	12 VDC			
Battery	RB12V7	RB12V7	RB12V7	RB12V7
Battery Qty*	1	2	3	4
Current Load	Power Backup Time (Hours)			
1 Amp	4.8	12.1	20.7	30.4
1.5 Amp	2.8	7	12.1	17.7
2 Amp	1.9	4.8	8.2	12
2.5 Amp	1.4	3.5	6.1	8.9
3 Amp	1.1	2.8	4.8	7
3.5 Amp	0.9	2.3	3.9	5.7
4 Amp	0.7	1.9	3.2	4.8

Standby Power	24 VDC**	
Battery	RB12V7	RB12V7
Battery Qty*	2	4
Current Load	Power Backup Time (Hours)	
1 Amp	4.8	12.1
1.5 Amp	2.8	7
2 Amp	1.9	4.8
2.5 Amp	1.4	3.5
3 Amp	1.1	2.8
3.5 Amp	0.9	2.3
4 Amp	0.7	1.9

[CLICK TO VIEW](#)

DOOR CONTROL MODULE CAPACITY***

Power Supply	634RFA	
Battery Qty*	0-2	3-6
VR	2	2
ACM	4	4
EMC	2	2
FB	4	4
UR1	4	4
CR	2	2
UR2	2	1
UR4	2	1
IPDC	1	-----
IPDS	1	-----

[CLICK TO VIEW](#)

* Battery quantity based on size of SDC's RB12V4 backup batteries.

** For 24 VDC standby power, minimum order of (2) batteries. Batteries must be ordered in pairs.


*** Total combined load of modules and access control hardware may not exceed power supply rating.

CERTIFICATIONS

- UL 1012 Power Units Other Than Class 2
- CSA-C22.2 No. 107.1 Power Conversion Equipment
- UL 2043 Fire Test for Heat and Visible Smoke Release for Discrete Products and Their Accessories Installed in Air-Handling Spaces

HOW TO ORDER

FOLLOW STEPS FOR ORDERING

 Designates optional step

1| SPECIFY MODEL
634RFA 4 Amp DC Power Controller With Large Cabinet

2| SPECIFY OPTIONS
220 230 VAC, 50/60 Hz
KL Key Lock Cover
MR Fire/Emergency Release Manual Reset Switch

3| SPECIFY ON/OFF
PS1 Power On/Off Inside Cabinet Enclosure
PS1A Power On/Off On Cabinet Enclosure Cover

4| SPECIFY BOARDS
VR Voltage Power Converter, 12VDC
ACM Six Input Control Relay
EMC Dual Channel Exit Device Sequencer
FB Four Output Power Distribution Module
UR1 Microprocessor Controller, Two Relays
CR Four Station Control Relay
UR2 Microprocessor Controller, Four Relays
UR4 Microprocessor Controller, Eight Relays
IPDC IPPro Controller, VR Included
IPDS IPPro Door Expansion, VR Included

STEP NUMBER:	1	2	3	4
ORDERING EXAMPLE:	634RFA	KL MR	PS1A	UR1 UR2

RELATED PRODUCTS

BACKUP BATTERIES

SDC power supplies equipped with batteries provide continuous operation of access controls, locking devices and peripheral components during a power failure.

[CLICK TO VIEW](#)

RB12V7 12V/7Ah Battery

RB12V7-2 12V/7Ah Battery, Qty 2 Pack

