# 490 Series

#### **Emergency Release Stations**





SDC's 490 series emergency release stations provide immediate unlocking of perimeter doors or interior doors that are equipped with fail-safe electric locks. The 490's built in alarm may be used as a local door annunciator.

Specifically designed for emergency door release, 490 series emergency release stations may influence the approval of an electric locking system.

The 491 model may be preferred over a pull station since greater commitment is required to break the glass.







492 492WP

#### **MODELS**

491 Emergency Break Glass Station

492 Emergency Pull Station

492WP Emergency Pull Station, Weatherized

### STANDARD FEATURES

- Blue housing eliminates confusion with red fire alarm stations
- · Easy to read activation instruction
- Integrated siren sounds upon activation\*
- Initiates release of individual door or all doors on same circuit
- Main contact for lock release
- Auxiliary contact for remote monitoring. CCTV or alarm activation
- Surface mount, single gang or double gang back box mount with plaster ring cover
- Two replacement glass pieces included









<sup>\* 491</sup> and 492 models only.

## SPECIFICATIONS

	491	492	492WP
Station	Break Glass	Pull	Pull, Weatherized
Housing	Painted Die Cast, Blue	Painted Die Cast, Blue	Painted Die Cast, Blue
Dimensions	5½" x 3½" x 1%"	4 <sup>3</sup> / <sub>4</sub> " × 3 <sup>1</sup> / <sub>4</sub> " × 1 <sup>3</sup> / <sub>8</sub> "	4¾" × 3¼" × 1¾"
Signage	DOOR RELEASE	DOOR RELEASE EMERGENCY	DOOR RELEASE EMERGENCY
	BREAK GLASS EMERGENCY	ALARM WILL SOUND	
	EXIT ALARM WILL SOUND		
Weight	2 lbs	2 lbs	2 lbs
Contact	SPDT (2)	SPDT (2)	SPDT (2)
Rating	10 Amp @ 30 VDC Resistive	10 Amp @ 30 VDC Resistive	10 Amp @ 30 VDC Resistive
Туре	Momentary (MO)	Momentary (MO)	Momentary (MO)
	Latches When Activated	Latches When Activated	Latches When Activated
Siren	3-28 VDC	3-28 VDC	
	18 mA	18 mA	

## CERTIFICATIONS

UL 38 Manual Signaling Boxes for Fire Alarm Systems CFSM Listed 150-0512:0006



#### FOLLOW STEPS FOR ORDERING

Designates optional step

#### 1| SPECIFY MODEL

491 Emergency Break Glass Station

492 Emergency Pull Station

492WP\* Emergency Pull Station, Weatherized

\* Backbox included.

STEP NUMBER:	1
ORDERING EXAMPLE:	491

## **RELATED PRODUCTS**

491-GL4 Replacement Glass Plates for 491, Quantity 4

**491-BB** Blue Surface Mount Back Box for 491, 51/4" x 31/4" x 11/2"

492-GL4 Replacement Glass Rods for 492, Quantity 4

**492-BB** Blue Surface Mount Back Box for 492, 43/4" x 31/8" x 15/8"



